

# MX-491BGD-B

## Emergency Door Release Break Glass Emergency Exit

The MICROAXS MX-491BGD-B Emergency Door Release Break Glass Station provides immediate unlocking of perimeter doors or interior doors that are equipped with fail-safe electric locks. The 491's built in alarm may be used as a local door annunciator.

The MICROAXS MX-491BGD-B is specifically designed for emergency door release and may influence the approval of an electric locking system. This type of Emergency Door Release may be preferred over a pull station since greater commitment is required to break the glass.



### Features

- Aluminum rod Blue housing with easy to read activation instructions avoids confusion with red fire alarm stations.
- The MICROAXS MX-491BGD-B may initiate the release of an individual door or all doors on the same circuit.
- The MICROAXS MX-491BGD-B may be mounted in a 2" deep single gang back box or double gang box with plaster ring cover. The MICROAXS MX-491BGD-B may be surface mounted with a surface mount back box.

### Specification

Model	MX-491BGD-B
Contacts	2-SPDT 10 Amp Contacts; 1-SPDT for lock release and 1-SPDT auxiliary contact for remote monitoring, CCTV activation or alarm activation
Aluminum Rod	For striking the glass is included. (Not required to break the glass)
Replacement Glass Plates	2 Replacement glass plates included
Dimension	5.5" H x 3.5" W x 1.375" D

